

Performance Chart for 12 volt Incandescent Bulbs

Bulb #	Bulb Life in Hours	Initial Lumen Output	Designed	Wattage/ Amps	Color (Kelvins)	Bulb Base	LED Replacment
			Lumen Output*				
93	500	189	75	13.3/1.04	2800-3000	BA15S	Single Contact Bayonet
68	5,000	50	20	8/59	2800-3000	BA15d	Double Contact Opposing Pins
94	800	50	20	8.06/62	2800-3000	BA15d	Double Contact Opposing Pins
211	300	121	48.4	12.42/.59	2800-3000	SV8.5-8	Festoon
212	300	75	30	10/.714	2800-3000	SV8.5-8	Festoon
847	300	278	111.2	25/2	2800-3000	BA15d	Double Contact Opposing Pins
904	5,000	50.24	20.096	9.3/.689	2800-3000	W2.1 x 9.5d	Wedge Based Bulb
906	1,000	75.36	30.144	9.3/.689	2800-3000	W2.1 x 9.5d	Wedge Based Bulb
912	1,000	150.72	60.288	12.8/1.000	2800-3000	W2.1 x 9.5d	Wedge Based Bulb
916	10,000	25.12	10.048	7.3/.541	2800-3000	W2.1 x 9.5d	Wedge Based Bulb
917	1,200	126	50.4	15.4/1.200	2800-3000	W2.1 x 9.5d	Wedge Based Bulb
918	500	81.64	32.656	7.2/.563	2800-3000	W2.1 x 9.5d	Wedge Based Bulb
920	1,200	126	50.4	15.4/1.200	2800-3000	W2.1 x 9.5d	Wedge Based Bulb
921	1,000	263.76	105.504	18/1.41	2800-3000	W2.1 x 9.5d	Wedge Based Bulb
922	200	188.4	75.36	12.5/.877	2800-3000	W2.1 x 9.5d	Wedge Based Bulb
923	500	151	60.4	11.6/.906	2800-3000	W2.1 x 9.5d	Wedge Based Bulb
1003	200	189	75	12/.938	2800-3000	BA15S	Single Contact Bayonet
1004	200	189	75.6	12/.94	2800-3000	BA15d	Double Contact Opposing Pins
1036	5,000	50	20	5/.42	2800-3000	SV8.5-8	Festoon
1073	300	255	160	21/1.8	2800-3000	BA15S	Single Contact Bayonet
1076	200	420	168	23.04/1.8	2800-3000	BA15d	Double Contact Opposing Pins
1093	100	188	76	15.2/1.19	2800-3000	BA15S	Single Contact Bayonet
1129	200	264	105	16.8/2.63	2800-3000	BA15S	Single Contact Bayonet
1141	500	220	104	18.4/1.44	2800-3000	BA15S	Single Contact Bayonet
1142	1,000	266.7	106.68	18.4/1.44	2800-3000	BA15d	Double Contact Opposing Pins
1152	500	266.7	106.68	17.2/1.34	2800-3000	BA15d	Double Contact Opposing Pins
1154	200	264	105	6.4/.5	2800-3000	BAY15d	Double Contact Index Pins
1156	1,200	402	160	26.9/2.1	2800-3000	BA15S	Single Contact Bayonet
1157	1,200	402	161	12.8/1.8	2800-3000	BAY15d	Double Contact Index Pins
1159	500	263	104	20.5/1.6	2800-3000	BA15S	Single Contact Bayonet
1196	300	635	254	37.5/3	2800-3000	BA15d	Double Contact Opposing Pins
1295	200	629	251	37.5/3	2800-3000	BA15S	Single Contact Bayonet
1459	300	31.4	12	3.2/.8	2800-3000	BA15S	Single Contact Bayonet
1619	500	188	76	12.7/1.9	2800-3000	BA15S	Single Contact Bayonet
1651	20	37.8	15.2	3/.6	2800-3000	BA15S	Single Contact Bayonet
1680	300	401	160.4	24.6/4.1	2800-3000	BA15S	Single Contact Bayonet
2057	1,200	402	161	12.8/1.8	2800-3000	BAY15d	Double Contact Index Pins
3423	150	99	39.6	5.07/.39	2800-3000	SV8.5-8	Festoon
3425	400	120	48	10/.833	2800-3000	SV8.5-8	Festoon
3497	600	565	226	25.2/2.1	2800-3000	BA15S	Single Contact Bayonet
5007	200	50	20	5/.417	2800-3000	BA15S	Single Contact Bayonet
5008	200	125	50	10/.833	2800-3000	BA15S	Single Contact Bayonet
6411	200	101	40.4	9.96/.83	2800-3000	SV8.5-8	Festoon
6413	200	101	40.4	5/.417	2800-3000	SV8.5-8	Festoon
6429	300	120	48	10/.417	2800-3000	SV8.5-8	Festoon
6451	75	220	88	15/1.25	2800-3000	SV8.5-8	Festoon
6475	300	242.57	97.028	18/1.5	2800-3000	SV8.5-8	Festoon
7506	300	464	185.6	21/1.75	2800-3000	BA15S	Single Contact Bayonet
7527	75	251	100.4	18/1.5	2800-3000	BA15S	Single Contact Bayonet

***Note - "Design Lumen Output"**

The incandescent bulbs, which our LED's replace, quickly degrade by 60% to the "Designed Lumen Output" listed on the chart. Thus, within just a few hours of use, many of these incandescent bulbs are less bright than our LED bulbs, but they still require 90% more amperage to run. Also, LED bulbs last 40,000-60,000 hours.

This manual has been provided courtesy of
My RV Works, Inc.

www.myrvworks.com



You can find more RV service manuals here:

www.myrvworks.com/manuals

Over the years of running a mobile RV repair service, having a dedicated place to access service manuals for all the different appliances and components found on RVs was something that I always had a desire to create.

I hope this resource makes your RV repairs easier, as it has mine, but please be careful and follow proper safety practices when attempting to repair your own RV.

If in doubt, please consult with a professional RV technician!



DARREN KOEPP - OWNER, MY RV WORKS, INC.

All service manuals provided on www.myrvworks.com are believed to be released for distribution and/or in the public domain.